

Part Number: 936010163

Product Description: GWconnect Turned Crimp Contact for 16A Inserts and Modules, Male, Silver (Ag) Plated Copper Alloy, 0.75mm² (18 AWG), 100 per Bag

Series Number: 93601

Status: Active

Product Category: Heavy-Duty Contacts

Engineering Number: 7300.6236.0



Product Environment Compliance

Compliance

| GADSL/IMDS | Not Relevant |
|--------------------|---|
| China RoHS | ® |
| EU ELV | Not Relevant |
| Low-Halogen Status | Low-Halogen per IEC 61249-2-21 |
| REACH SVHC | Contains Lead per D(2022)9120-DC (17 Jan 2023) |
| EU RoHS | Compliant with Exemption 6(c) per EU 2015/863 |

Multiple Part Product Compliance Statements

- Eu RoHS
- REACH SVHC
- Low-Halogen

Multiple Part Industry Compliance Documents

- IPC 1752A Class C
- IPC 1752A Class D
- Molex Product Compliance Declaration
- IEC-62474
- chemSHERPA (xml)

EU RoHS Certificate of Compliance

ZZCERT CE - Declaration of Conformity: CER 4000443879 00 000.pdf ZZCERT_UKCA - Declaration of Conformity: CER_4000443911_00_000.pdf

Part Details

General

| Status | Active |
|----------------|---|
| Category | Heavy-Duty Contacts |
| Series | 93601 |
| Description | GWconnect Turned Crimp Contact for 16A Inserts and Modules, Male, Silver (Ag) Plated Copper Alloy, 0.75mm ² (18 AWG), 100 per Bag |
| Contact Type | Turned Crimp |
| Product Family | GWconnect Heavy Duty Connectors (HDC) |
| Product Name | GWconnect |
| UPC | 887191874319 |

Agency

| CSA | 256883 |
|-----|---------|
| UL | E249674 |

Electrical

| Current - Maximum per Contact | 16.0A |
|-------------------------------|----------|
| carrette maximam per contact | 1 0.07 (|

Physical

| Gender | Male |
|--------------------|--------------|
| Material - Contact | Copper Alloy |
| Material - Plating | Silver |
| Net Weight | 1.200/g |
| Number of Grooves | 1 |
| Packaging Type | Bag |
| Stripping Length | 7.50mm |
| Wire Size (AWG) | 18 |
| Wire Size mm² | 0.75 |

Mates With / Use With

Mates with Part(s)

| Description | Part Number |
|---|--------------|
| GWconnect Heavy-Duty Connectors and Accessories | <u>93601</u> |

Use with Part(s)

| Description | Part Number |
|-------------|--|
| Use With | S-AC, S-EC, S-EE, S-EEE, S-EHV,S-Q, S-QD, and S-M Inserts |

This document was generated on Aug 01, 2023